

Zero Biased Waveguide Detector With WR-10 to SMA Female and Negative Video Out Operating From 75 GHz to 100 GHz W Band, UG-387/U

FMMT3000 is a W Band Waveguide Detector. The Detector operates in the 75 GHz to 100 GHz Frequency Range and has a Negative Output with a Sensitivity of -500 mV/mW Minimum and -900 mV/mW Typical. The unit operates over a 0°C to +50°C Temperature Range and has a Maximum Input Power Rating of +20 dBm. The Detector has a WR-12 Waveguide with UG 387/U Flange as the RF connector and the DC Output Port uses an SMA Female Connector.

Electrical Specifications

Description	Min	Typ	Max	Unit
Frequency Range	75		100	GHz
Voltage Sensitivity	-500	-900		mV/mW
Input Power			+20	dBm

Mechanical Specifications

Temperature

Operating Range 0 to +50 deg C

Size

Length 1.24 in [31.5 mm]
 Width 1 in [25.4 mm]
 Height 0.75 in [19.05 mm]
 Weight 0.0625 lbs [28.35 g]
 RF Connector WR-10 Waveguide with UG-387/U Flange
 DC Connector SMA Female

Compliance Certifications (visit www.FairviewMicrowave.com for current document)

Plotted and Other Data

Notes:

- Values at 25 °C, sea level
- ESD Sensitive Material, Transport material in Approved ESD bags. Handle only in approved ESD Workstation.



Features:


- Frequency: 75 GHz to 100 GHz
- Sensitivity: -500 mV/mW Minimum; -900 mV/mW Typical
- Maximum Power Input 20 dBm
- RF Connector WR-10 Waveguide with UG 387/U Flange

Applications:

- Test Lab
- Military Communications
- Commercial Communications

Fairview Microwave
 1130 Junction Dr. #100
 Allen, TX 75013
 Tel: 1-800-715-4396 / (972) 649-6678
 Fax: (972) 649-6689
www.fairviewmicrowave.com
sales@fairviewmicrowave.com

Typical Performance Data




Zero Biased Waveguide Detector With WR-10 to SMA Female and Negative Video Out Operating From 75 GHz to 100 GHz W Band, UG-387/U from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Allen, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: [Zero Biased Waveguide Detector With WR-10 to SMA Female and Negative Video Out Operating From 75 GHz to 100 GHz W Band, UG-387/U FMMT3000](#)

URL: <http://www.fairviewmicrowave.com/zero-biased-waveguide-detector-wr-10-sma-female-negative-75-100-ghz-fm-mt3000-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.



UNLESS OTHERWISE SPECIFIED:
 DIMENSIONS ARE IN: inches
 TOLERANCES ARE: [mm]
 .XX ± .01 [±.25]
 .XX ± .001 [±.025]

* THESE DIMENSIONS AND TOLERANCES
 SUPERSEDE NOTE #1 ON TITLE BLOCK.

FAIRVIEW MICROWAVE INC. ALLEN, TX 75013 WWW.FAIRVIEWMICROWAVE.COM		NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm].			
TITLE Zero Biased Waveguide Detector With WR-10 to SMA Female and Negative Video Out Operating From 75 GHz to 100 GHz W Band, UG-387/U		DWG NO FMMT3000		CAGE CODE 3FKR5	
CAD FILE	071715	SHEET	SCALE	N/A	SIZE A 2233